WASHA-MESHA BIGHTER

取扱説明書

注意事項 Technical information

(1)電源

Required Power Capacity +5V 5A or more +12V 1A or more

(2)Output

R-analog, positive

G-analog, positive B-analog, positive

SYNC-H-V complexed, negative

あそびかた Play Instruction



ジョイスティックレバー8方向 8-WAY LEVER



PUSH 1

ショット

SHOT

びっぐ BIG

PUSH 2

半 田 面 SOLDER SIDE	•		部 品 面 COMPONENT SIDE
GND	Α	1	GND
GND	В	2	GND
+5V	С	3	+5V
+5V	D	4	+5V
	E	5	
+12V	F	6	+12V
	Н	7	
COIN COUNTER2	J	8	COIN COUNTER1
	К	9	
SP(-)	L	10	SP(+)
	M	11	
VIDEO GREEN	N	12	VIDEO RED
VIDEO SYNC	Р	13	VIDEO BLUE
SERVICE SW	R	14	VIDEO GND
	S	15	
COIN SW 2	Т	16	COIN SW 1
START SW 2	υ	17	START SW 1
2P UP	V	18	1P UP
2P DOWN	W	19	1P DOWN
2P LEFT	Х	20	1P LEFT
2P RIGHT	Υ	21	1P RIGHT
2P PUSH 1	Z	22	1P PUSH 1
2P PUSH 2	а	23	1P PUSH 2
	b	24	
	С	25	
	d	26	
GND	е	27	GND
GND	i	28	GND

JAMMA仕様

DHU	SHOTが一段階UP (最大7段階)	ONE-STEP-UP-SHOT MAX. 7 STEPS	Pow
Wed was	小機が一機ふえます (最大4コ)	INCREASE ONE MORE SMALL SELF-CHARACTOR MAX. 4 PCS	noi fa
₩ \$\@	一定時間無敵で 超最大SHOT!!	INVINCIBLE for a while ULTRA-BIGEEST SHOT	Bis
Beilte N&C	オプションと パワーが最大	OPTION & MAX. POWER	Super Wod

サウンドボリューム
Sound ajustment

「ニー・ディップスイッチ2
DIP SW 2
「ニー・ディップスイッチ1
DIP SW 1

ディップスイッチ DIP SWITCH HACHA-MECHA FIGHTER

DIP SWITCH 1		1	2	3	4	5	6	7	8	
		3	OFF	OFF						
プレイヤー数		2	ON	OFF						
PLAYER'S NUMBER		4	OFF	ON						
		1	ON	ON						
	普通	NORMAL					OFF	OFF		
難易度 DIFFICULTY 非	易しい	EASY					ON	OFF		
	難しい	HARD					OFF	ON		
	非常に難しい	HARDEST					ON	ON	-	
表示語	日本語	JAPANESE							OFF	
LANGUAGE	英語	ENGLISH							ON	
画面反転	無し	NO .								OF
SCREEN F/F	有り	YES								10
出荷時の設定	SETTING AT MAKER'S	DELIVERY	OFF	OF						

	DIP SWITCH 2	1	2	3	4	5	6	7	8
	1 COIN 1 PLAY		OFF	OFF			-		-
	1 COIN 2 PLAY	ON	OFF	OFF					-
	1 COIN 3 PLAY	OFF	ON	OFF					-
COIN SW 1	1 COIN 4 PLAY	ON	ON	OFF					-
30117 0117 1	2 COINS 1 PLAY	OFF	OFF	ON					
	3 COINS 1 PLAY	ON	OFF	ON					-
	4 COINS 1 PLAY	OFF	ON	ON					
	FREE PLAY	ON	ON	ON					
	1 COIN 1 PLAY				OFF	OFF	OFF		
	1 COIN 2 PLAY				ON	OFF	OFF		
	1 COIN 3 PLAY				OFF	ON	OFF		
COIN SW 2	1 COIN 4 PLAY				ON	ON	OFF		-
55111 511 2	2 COINS 1 PLAY				OFF	OFF	ON		
	3 COINS 1 PLAY				ON	OFF	ON		
	4 COINS 1 PLAY				OFF	ON	ON		
	FREE PLAY				ON	ON	ON		
デモ時のサウンド	有り YES							OFF	
EMONSTRATION SOUND	無し NO							ON	
出荷時の設定 SET	TING AT MAKER'S DELIVERY	OFF	OF						

